

POWER UP MODES

HOLD DOWN:

+-----+ Hz +-----+	-	Extends autoranging frequency to > 200 kHz
+-----+ dB +-----+	-	Increases resolution in dB (below 1024 counts), Megohms (above 100 megohms), and Auto Kohms (above 100 kohms)
+-----+ CONT +-----+	-	Self diagnostic a/d converter test Display should read 10000 \pm 5 counts
+-----+ REL +-----+	-	Self diagnostic switch test

FUNCTIONS NOT ON THE DECAL

HIGH-Z MODE:

200 mV or 2 V DC
> 10000 megohms, 80000 megohms typical

SELECTION:

Release all three function switches (AC/DC, V, Ohms)
Select either the 200 mV or 2 V ranges

AUTO-RANGING KOHMS:

Provides a range that covers from .1 ohm to 300 kohms, fully autoranging in under 1 second

SELECTION:

Press M_Ω and the 200 Ω buttons simultaneously while in ohms mode

2000 MICROSIEMENS CONDUCTANCE RANGE:

An inverse resistance range that covers from 500 ohms to 10 megohms. Accuracy... \pm (.15% reading + 5 counts)

SELECTION:

Press M_μ, 200 k_μ, and 200 Ω buttons simultaneously while in the ohms mode