

WaveRunner 6000(A) SDVO card LVDS pinout & Kontron mapping (20 wires cable)

J1 SDVO	Front Panel		CBL#	Kontron JILI40			
1	GND	GND	1	1	12V	12V	2
2	GND	GND	2	3	12V	12V	4
3	SHORTED	NC	NC	5	12V	GND	6
4	SHORTED	NC	NC	7	5V	GND	8
5	GND	GND	3	9	LCD VDD	LCD VDD	10
6	CLKA+	CLKA+	4	11	DDC CLK	DDC DATA	12
7	CLKA-	CLKA-	5	13	BKL CTL	VDD EN	14
8	GND	GND	NC	15	BKL EN	GND	16
9	A2+	A2+	6	17	A0-	A0+	18
10	A2-	A2-	7	19	A1-	A1+	20
11	GND	GND	NC	21	A2-	A2+	22
12	A1+	A1+	8	23	CLKA-	CLKA+	24
13	A1-	A1-	9	25	A3-	A3+	26
14	GND	GND	NC	27	GND	GND	28
15	A0+	A0+	10	29	B0-	B0+	30
16	A0-	A0-	11	31	B1-	B1+	32
17	GND	GND	12	33	B2-	B2+	34
18	GND	GND	13	35	CLKB-	CLKB+	36
19	LCD VDD	LCD VDD	14	37	B3-	B3+	38
20	LCD VDD	LCD VDD	15	39	GND	GND	40

16	17
18	19
15	14
20	13
11	10
9	8
7	6
5	4
12	3
2	1

J2 SDVO			
1	12V	Yellow	16,17
2	GND	Black	18,19
3	BKL EN	White	20
4	NC		
5	NC		